



ALLOCCIO, BACCHINI e Co.
 Mod. 611 e 612. - Gamme: 12-16,
 16-22, 21-295, 28-40, 37-52 e m
 1650-520 kHz. - v. Tabella.

VALORI DEI CONDENSATORI

C1/C8/C26	100	PF	C23/C24	150	PF
C2/C3/C17	0,2	MF	C27	0,25	MF
C4/C5/C6/C7	0,1	MF	C28	50000	PF
C9	480	PF	C29/C33	10	MF
C10	1050	PF	C34	16	MF
C11	1600	PF	C35	16	MF
C12	2100	PF	C36	16	MF
C13	2500	PF	C37	16	MF
C14/C25	50	PF	C38	5000	PF
C15/C16	150	PF	C39	5000	PF
C18/19/C21	0,2	MF	C40	0,1	MF
C22	0,2	MF			

VALORI DELLE RESISTENZE

R1/R3	0,1	M	1/2 W	R15/R16	1 M	1/2 W
R2	250 ohm		1/2 W	R17	0,25	1/4 W
R4/R9	2000 ohm		1/2 W	R18/R28	50000	1/2 W
R5	150	"	1/2 W	R19	1 M	1/2 W
R6/R11	50000	"	1/2 W	R21	100	1/2 W
R7/R20	5000	"	1/2 W	R22	1,5 M	potenz.
R8	25000	"	1 W	R23	0,2	1/2 W
R10/R26	500	"	1/2 W	R24	0,5	1/2 W
R12	10000	"	potenz.	R25	2500	poten.
R13	10000	"	4 W	R27	300	2 W
R14	10000	"	1/2 W	R29	5000	1/2 W