



**RESISTORS**

R1	13041	800 ohm—1/2 w.
R2	13017	10M ohm—1/2 w.
R3	13020	100M ohm—1/2 w.
R4	13012	50M ohm—1/2 w.
R5	13017	10M ohm—1/2 w.
R6	13031	1500 ohm—1/2 w.
R7	13042	20M ohm—1/2 w.
R8	1304	3 megohm—1/2 w
R9	10126	1 megohm control
R10	130233	60 ohm—1/2 w.
R11	1304	3 megohm—1/2 w.
R12	130203	40 ohm—1/2 w.
R13	1309	200M ohm—1/2 w.
R14	13019	1 megohm—1/2 w.
R15	130232	25M ohm—1/2 w.

**CONDENSERS**

CA	Adjustable Capacitor
CB	Adjustable Capacitor
C	2 gang variable condenser
C1	.000105 Mica
C2	.00009 Mica
C3	.003 x 600 v.
C4	SW. Antenna Trimmer 2.25 mmfd.
C5	BC. Antenna Trimmer 1-10 mmfd.
C6	.05 x 400 v.
C7	SW. Oscillator Trimmer 2-25 mmfd.
C8	BC. Oscillator Trimmer 2-25 mmfd.
C9	.00005 Mica
C10	.002 x 600 v.
C11	350 mmfd. W.C. B.C. Series Pad
C12	.0041 Compression Type
C13	.25 x 400 v.
C14	.00005 Mica
C15	.01 x 400 v.
C16	.0005 Mica
C17	.01 x 400 v.
C18	.05 x 400 v.
C19	8 mfd.—350 v. v. lytic
C20	12 mfd.—350 v. v. lytic

**PARTS**

T1 SW. B. C. Antenna Coil Complete  
T2 SW. B. C. Oscillator Coil Complete  
T3 Input I. F.—465 kc.  
T4 Output I. F.—465 kc.  
T5 Output Transformer  
T6 Power Transformer  
T7 6" Speaker Dynamic (1500 ohm field)  
S1 Band Switch  
S2 Off-on Switch on volume control  
P1 6.3 v. Pilot Light T-44

A - CANNOT BE MEASURED WITH VOLTMETER  
B - BIAS OF -1.8V READ ACROSS R-12  
C - BIAS OF -2.8V READ ACROSS R-10  
E - 5V AC READ ACROSS TER. 2 & 8  
F - 560V AC READ ACROSS TER. 4 & 6

**REAR OF CHASSIS**

Belmont Radio

**MODEL 665**

