

Sears, Roebuck & Co.
Chicago.

Models 6158, 6159,
6192.

WAVE BAND-SWITCH POSITION	POSITION OF VARIABLE	GENERATOR FREQUENCY	DUMMY ANTENNA	GENERATOR CONNECTION	TRIMMERS ADJUSTED (IN ORDER SHOWN)	TRIMMER FUNCTION	APPROXIMATE MICROVOLTS
"AM"	Closed	455 kc	.1 mfd.	6A8G Grid	T2, T1	IF Output IF Input	810
"SW"	15 mc(rock)	15 mc	400 ohms.	Ant. Term.	C13	Translator	40
"9"	9.55 mc	9.55 mc	400 ohms.	*Ant. Term.	C9*	Oscillator	60
"11"	11.71 mc	11.71 mc	400 ohms.	Ant. Term.	C16	Translator	40
"15"	14.9 mc	14.9 mc	400 ohms.	Ant. Term.	C7*	Oscillator	40
"AM"	1400 kc	1400 kc	.0002 mfd.	Ant. Term.	C15	Translator	40
"AM"	600 kc(rock)	600 kc	.0002 mfd.	Ant. Term.	C5*, C14	Oscillator Translator	40
"AM"					C17, C12, C1	Osc., Transl., RF	30
"AM"					C18	Padder	40

WIRING DIAGRAM FOR SILVERTONE CHASSIS 101.555

