



DIAGRAM NUMBER	PART NUMBER	DESCRIPTION
1-2	83539	Condenser - mica 280 mfd.
3	85061	Condenser - mica 51 mfd.
4	88686	Condenser - mica 200 mfd.
5	112971	Resistor - insulated, 470,000 ohm 1/2 watt
6	112987	Resistor - insulated, 220,000 ohm 1/2 watt
7	116050	Resistor - insulated, 10 meg. 1/2 watt
8	116056	Resistor - 2.2 meg. 1/2 watt
9	116059	Resistor - insulated, 22,000 ohm 1/2 watt
10	116092	Resistor - 140 ohm, 1 watt-wire wound
11-12	116819	Condenser - .05 mfd. 600 volt
13	118921	Lamp-Dial (Mazda #47)
14-15	119193	Condenser - .01 mfd. 600 volt
16	119875	Condenser - .002 mfd. 600 volt
17A-17B	500223	Volume Control - 1 meg. (with switch)
18	501388	Loop Antenna
19A-19B	501223	Condenser - trimmer (2 sections) (A-35 mfd.) (B-238 mfd.)
20	501157	Coil - antenna (with slug)
21	501158	Coil - oscillator (with slug)
22	501166	Transformer - 2nd I.F.
23	501233	Transformer - 1st I.F.
24	R-500916	Speaker - dynamic (4")
25	R-501163	Transformer - output for R-500916 Spkr.
26	R-501164	Cone & Voice Coil for R-500916 Spkr.
27A-27B	501213	Electrolytic Condenser (A-40 mfd. - 150 volt) (B-20 mfd. - 150 volt)

STEWART-WARNER 205G CHASSIS MODELS 205GA TO 205GZ

