Item No.	Part No.	Description	Item No.	Part No.	Description
2	C-132300-1	Cable and Plug Assy., Power	21	39373-60	Resistor, 22,000 ohm, ½ w.
3	AC-135209	Loop and Back Assy., Antenna	23	39373-100	Resistor, 3.3 megohm, ½ w.
4	AW-135195	Coil Assy., Oscillator	25	39373-144	Resistor, 1200 ohm, 1 w.
5	AW-137665	Transformer, 1st I. F.	26	39373-102	Resistor, 4.7 megohm, ½ w.
6	AW-137667	Transformer, 2nd I. F.	27	39373-87	Resistor, 470,000 ohm, ½ w.
8 A	B-135056	Condenser, Variable } Two	28	39373-87	Resistor, 470,000 ohm, ½ w.
8 B		Condenser, Variable } Section	29	39373-16	Resistor, 150 ohm, ½ w.
8 C	Part of Item #8A	Condenser, Trimmer	30 A	C-135127	Control, Volume (1 megohm) } Assy.
8 D	Part of Item #8B	Condenser, Trimmer	30 B		Switch, Power }
9	39001-17	Condenser, .05 mfd., 600 v., paper	*	39368-14	Control, Volume
10	39001-17	Condenser, .05 mfd., 600 v., paper	*	39369-1	Switch, Power
12	39001-73	Condenser, 250 mmf., 600 v., paper	31	B-137723	Transformer, Ouput
13	39001-73	Condenser, .003 mfd., 600 v., paper	33	W-137367	Resistor, 47 ohm, 1 w.
14	39001-80	Condenser, .02 mfd., 600 v., paper	34	Part of Item #6	Resistor, 47,000 ohm, ½ w.
15	39001-80	Condenser, .02 mfd., 600 v., paper		W-135164	Bumper, Rubber
17	B-136768	Speaker		R-135162	Cabinet, (57TK)
18	39001-17	Condenser, .05 mfd., 600 v., paper		AW-135246	Cabinet, (57TL)
19 A	B-136770	Cond'ser, 50 mfd., 150 v. } Two Sect.		W-131154-1	Cotter, External
19 B		Cond'ser, 30 mfd., 150 v. } Elec. Filter		B-135713	Dial Glass
20	39373-109	Resistor, 15 megohm, ½ w.		W-134055	Grommet, Var. Cond. Mtg



MODELS: 57TK, 57TL

NOTES:
1. These are bottom views of tube sockets.
2. Measure voltages from socket lugs to -B (pin 4 on the 14A7).
3. These voltages were measured using an electronic voltmeter. Line voltage 117.
4. W.J. = Wiring junction
5. N.C. = No connection
6. * = 60 cycle A.C. voltages.
7. Socket voltage tolerance 10%.



CROSLEY

MODELS: 57TK, 57TL