



I.F. = 262 K.C.
 FREQ. RANGE —
 545 KC TO 1600 KC

- | | | | | | |
|----|----------|--|----|----------|-----------------------------------|
| 1 | 1X263L7 | ANTENNA COIL & SHIELD ASSEMBLY | 31 | 66625L | CARBON RESISTOR (330-1-10) INS. |
| 2 | 2LA2352 | R.F. COIL & SHIELD ASSEMBLY | 32 | 666010 | CARBON RESISTOR (330-1/2-20) INS. |
| 3 | 1X263L5 | OSCILLATOR COIL | 33 | 66603L6 | CARBON RESISTOR (300-1/3-10) INS. |
| 4 | 1X263L5 | I.F. COIL & SHIELD ASSEMBLY | 34 | 666005 | CARBON RESISTOR (50-1/2-20) N.I. |
| 5 | 1X263L3 | DIODE COIL & SHIELD ASSEMBLY | 35 | 666005 | CARBON RESISTOR (50-1/2-20) N.I. |
| 6 | 25B1799L | OUTPUT TRANSFORMER | 36 | 8A17072 | TUBULAR CONDENSER (.5-100V.) |
| 7 | 25B17770 | INPUT CHOKER (SHIELDED) | 37 | 8A3374 | TUBULAR CONDENSER (.25-100V.) |
| 8 | 25B17975 | POWER TRANSFORMER | 38 | 8K13166 | TUBULAR CONDENSER (.1-100V.) |
| 9 | 2JA17819 | VIBRATOR CHOKER | 39 | 8A117791 | TUBULAR CONDENSER (.05-100V.) |
| 10 | 2K2003 | TUBULAR "A" CHOKER | 40 | 8A13514 | TUBULAR CONDENSER (.05-100V.) |
| 11 | 2LX17818 | FILAMENT CHOKER | 41 | 8A13514 | TUBULAR CONDENSER (.05-100V.) |
| 12 | 50B2039 | SPEAKER (7" ELECTRO) | 42 | 8A1351L | TUBULAR CONDENSER (.05-100V.) |
| 13 | 19K263L2 | VARIABLE CONDENSER (3 GANG) | 43 | 8A12841 | TUBULAR CONDENSER (.05-300V.) |
| 14 | 20K26392 | OSCILLATOR PADDER (325 MFD. NOM.) | 44 | 8A12841 | TUBULAR CONDENSER (.05-300V.) |
| 15 | 23A17730 | ELECTROLYTIC COND. (15-10/350V.-20/25V.) | 45 | 8A10432 | TUBULAR CONDENSER (.01-1000V.) |
| 16 | 666159 | CARBON RESISTOR (1.0 MEG-1/3-20) INS. | 46 | 8A11000 | TUBULAR CONDENSER (.01-100V.) |
| 17 | 666159 | CARBON RESISTOR (1.0 MEG-1/3-20) INS. | 47 | 8K13165 | TUBULAR CONDENSER (.005-1000V.) |
| 18 | 66628L | CARBON RESISTOR (15,000-1/3-20) INS. | 48 | 21B6500 | MOLDED MICA COND. (500 MFD.) 20% |
| 19 | 666159 | CARBON RESISTOR (1.0 MEG-1/3-20) INS. | 49 | 8A12699 | TUBULAR CONDENSER (.02-100 V.) |
| 20 | 666256 | CARBON RESISTOR (68,000-1/3-20) INS. | 50 | 21A126L3 | CERAMIC CONDENSER (50 MFD) |
| 21 | 666355 | CARBON RESISTOR (39,000-1/2-20) INS. | 51 | 18A17767 | VOL. CONT. & SWITCH (1.5 MEG.) |
| 22 | 666012 | CARBON RESISTOR (22,000-1/3-20) INS. | 52 | 10A26887 | TOUCH CONTROL SWITCH (3 POS.) |
| 23 | 666212 | CARBON RESISTOR (22,000-1/3-20) INS. | 53 | 18A5067 | VIBRATOR |
| 24 | 666271 | CARBON RESISTOR (15,000-1-20) INS. | 54 | 65A1165 | FUSE (15 AMP.) 3AG |
| 25 | 666353 | CARBON RESISTOR (2200-1/3-10) INS. | 55 | 1X2181 | DIAL LIGHT ASSEMBLY |
| 26 | 66618L | CARBON RESISTOR (1000-1-20) N.I. | 56 | 1X17868 | FUSE LEAD ASSEMBLY |
| 27 | 666217 | CARBON RESISTOR (720-1/3-10) INS. | 57 | 65A1151 | BULB (WHITE BEAD) 451 |
| 28 | 666386 | CARBON RESISTOR (680-1/3-10) INS. | | | |

Motorola

Model 401

