



PHONOLA (S. A. FIMI). — Mod. « 539 », « 540 » e « 541 ». — Produzione 1939-1940. — Media frequenza: 470 kHz. Potenza resa: 4 W. — Consumo: 55 W sopramobile; 75 W radiofonografo.

PHONOLA 539

CAPACITÀ

RESISTENZE

Nomin.	Valore	Tolleranza %	Tensione di prova	Tipo	Nomin.	Valore	Toll. %	Watt
1	15 pf	±10		Ag.	R 1	2 M Ω	±10	1/4
2	5 pf	±10		Ag.	R 2	200 Ω	±10	1/4
3	20 pf	±10		Ag.	R 3	20.000 Ω	±10	1/4
4	0,05 μ	±10	1500		R 4	1 M Ω	±10	1/4
5	0,1 uf	±10	1000		R 5	1 M Ω	±10	1/4
6	100 pf	±10		Ag.	R 6	50.000 Ω	±10	1/4
7	0,1 uf	±10	1500		R 7	30.000 Ω	±10	1/4
8	440 pf	±1		Ag.	R 8	50 Ω	±10	1/4
9	240 pf	±1		Ag.	R 9	30.000 Ω	±10	1/4
10	500 pf	±5	1500		R 10	2 M Ω	±10	1/4
11	2 pf	±10		Ag.	R 11	50.000 Ω	±10	1/4
12	240 pf	±10	1500	Ag.	R 12	300.000 Ω	±10	1/4
13	5.000 pf	±10	>		R 13	300.000 Ω	±10	1/4
14	50.000 pf	±10	>		R 14	1 M Ω	±10	1/4
15	2.000 pf	±10	3000		R 15	2 M Ω	±10	1/4
16	0,1 uf	±10	1500		R 16	25 Ω	±10	1/4
17	2.000 pf	±10	3000		R 17	2 M Ω	±10	1/4
18	240 pf	±10		Ag.	R 18	100.000 Ω	±10	1/4
19	0,1 uf	±10	1500		R 19	5.000 Ω	±10	1/4
20	1,2 pf	±10	>		R 20	50 Ω	±10	1/4
21	500 pf	±10	>		R 21	25 Ω	±10	1/4
22	240 pf	±10	>	Ag.	R 22	150.000 Ω	±10	1/4
23	100 pf	±10		Ag.	R 23	100.000 Ω	±10	1/4
24	0,1 uf	±10	1500		R 24	50.000 Ω	±10	1/4
25	100 pf	±10		Ag.	R 25	1.650 Ω	±10	1/4
26	10.000 pf	±10	1500					
27	0,5 uf	±10	1000					
28	500 pf	±10	1500					
29	500 pf	±10	>					
30	4 uf	+30 - 20	575	Elettrolitico				
31	25.000 pf	±10	1500					
32	25.000 pf	±10	>					
33	25.000 pf	±10	>					
34	5.000 pf	±10	3000					
35	8 uf	+30 - 20	575	Elettrolitico				
36	8 uf	+30 - 20	>	Elettrolitico				
37	1,000 pf	±10	1500					
38	10 pf	±10		Ag.				
39	5 pf	±10		Ag.				

R V	-	1 M Ω	Esponenziale
R T	-	0,1 M Ω	Esponenziale con Interruttore

● Eccitazione altoparlante