



Wilcox-Gay Corporation, Charlotte, Mich.

Model A-53
COND. (Cont.)

RESISTORS

R1	53-898	50,000 Ohm	1/4 Watt Resistor
R2	53-1062	250 Ohm	1/2 Watt Resistor
R3	53-928	1 Meg Ohm	1/4 Watt Resistor
R4	20-2011	154 Ohm	1/4 Watt Resistor
R5	53-2016	26 Ohm	2.34 Watt Resistor
R6	53-1042	25,000 Ohm	1/4 Watt Resistor
R7	19-2012	500,000 Ohm	Volume Cont. & Switch
R8	53-913	5,000 Ohm	1/4 Watt Resistor
R9	53-925	500,000 Ohm	1/4 Watt Resistor
R10	53-924	250,000 Ohm	1/4 Watt Resistor
R11	53-925	800,000 Ohm	1/4 Watt Resistor
R12	53-2014	200 Ohm	1/4 Watt Resistor

CONDENSERS

C1	75-2003	.01 Mfd 400 V. Paper Cond.
C2, C3	77-2015	Two Gang Variable Condenser
C4	76-2302	.00005 Mfd Mica Condenser
C5	75-2005	.1 Mfd 200 V. Paper Cond.
C6	75-2005	.1 Mfd 200 V. Paper Cond.
C7	75-2005	.1 Mfd 200 V. Paper Cond.
C8	76-307	.0005 Mfd Mica Condenser
C9	75-2003	.01 Mfd 400 V. Paper Cond.
C10	16-2012	10 Mfd 25 W. V. Dry Elect. Cond.
C11	75-2014	.301 Mfd 600 V. Paper Cond.
C12	75-2003	.01 Mfd 400 V. Paper Cond.
C13	75-2001	.002 Mfd 600 V. Paper Cond.
C14	18-2012	10 Mfd 25 W. V. Dry Elect. Cond.

C15	18-2011	8 Mfd 150 W.V. Dry Elect. Cond.
C16	18-2011	8 Mfd 150 W.V. Dry Elect. Cond.
C17	13-2010	16 Mfd 150 W.V. Dry Elect. Cond.
C18	75-2005	.1 Mfd 200 V. Paper Condenser
L1	17-2232	Oscillator Coil Assembly
L2	17-2230	Preselector Coil Assembly
L3	58-2055	First I.F. Trans. Assembly
L4	58-2052	Second I.F. Trans. Assembly
L5	64-2043	5" Speaker, Output Trans. for 25L6 Tube
L6	64-2043	3000 Ohm Field on L5
L7	14-2202	18 Henry Filter Choke