



DIAG. NO.	PART NO.	DESCRIPTION	DIAG. NO.	PART NO.	DESCRIPTION	DIAG. NO.	PART NO.	DESCRIPTION	DIAG. NO.	PART NO.	DESCRIPTION
C1	22-878	TWO-GANG VARIABLE	C19	22-865	COMPENSATING COND.	R14	63-586	3500 OHM	A		121 I.F. TRANS. PRI.
C2	22-889	50 MMFD.	C20	22-700	OSC. PADDER	R15	63-605	1000 OHM	B		121 I.F. SEC.
C3	22-889	.05 MFD.				R16	63-1036	3-SECTION CANOVM	C		221 I.F. PRI.
C4	22-350	.25 MFD.				R17	63-1012	90 OHM WIREWOUND	D		221 I.F. SEC.
C5	22-196	.01 MFD.				1	57257	ANTENNA COIL ASSEMBLY	E		BDCAST OSC. (SEE NOTE)
C6	22-182	100 MMFD.	R1	63-654	180M OHM	2	57252	OSC. COIL ASSEMBLY	F		ANT. BDCAST (ON GANG)
C7	22-826	.01 MFD.	R2	63-592	47M OHM	3	56992	OSC. COUPLING COIL ASSEM.	G		BDCAST PADDER (SEE NOTE)
C8	22-927	1MFD.	R3	63-597	470M OHM	4	57044	AUTO TUNING UNIT ASSEM.	H		S.W. OSC. (SEE NOTE)
C9	22-887	.001 MFD.	R4	63-649	35M OHM	5	85-195	BAND SELECTOR SW.	J		S.W. DETECTOR
C10	22-243	.01 MFD.	R5	63-296	220M OHM	6	95-607	121 I.F. TRANSFORMER	K		POL. BAND OSC. (SEE NOTE)
C11	22-440	.004	R6	63-669	39 MEGOHM	7	95-614	221 I.F. TRANSFORMER	L	22-700	
C12	22-980	120 MFD. ELECTROLYTIC	R7	63-1087	VOLUME CONTROL	8	56994	TONE CONTROL SW.			
C13	22-880	20 "	R8	63-587	4700 OHM	9	85-195	POWER SW.			
C14	20 "	"	R9	63-591	22M OHM						
C15	22-879	60 MFD.	R10	63-604	10 MEGOHM						
C16	60 "	"	R11	63-271	1 MEGOHM						
C17	22-869	.05 MFD.	R12	63-600	2.2 MEGOHM						
C18	22-350	.002 MFD.	R13	63-640	8200 OHM						

MODEL	SPEAKER
5G441	49-316 8"
5G442	49-317 10"
5G461	49-318 10"

I.F. FREQUENCY 455 KC
 5 TUBE SUPERHETERODYNE
 110V. A.C. - BATT. PACK - UNIVERSAL
 CHASSIS NO. 5539 - 3 BAND
 ZENITH RADIO CORPORATION
 CHICAGO, ILL.

MODELS 5G441, 5G442, 5G461 (Chassis No. 5539)

NOTE - TRIMMERS E, J, K, N ARE MOUNTED ON STRIP *22-801.