



DIAG. NO.	PART NO.	DESCRIPTION	DIAG. NO.	PART NO.	DESCRIPTION	DIAG. NO.	PART NO.	DESCRIPTION
C1	22-1201	THREE-GANG VARIABLE	R3	63-589	10M OHM	A	95-808	1ST I.F. TRANS.
C2	22-829	.05 MFD.	R4	63-976	15 MEG OHM	B	98-809	2ND I.F. TRANS.
C3	22-1017	.05 MFD.	R5	63-600	2.2 MEG OHM	C	100-67	PILOT LIGHT 6.3 V. .15A.
C4	22-243	.01 MFD.	R6	63-1112	VOLUME CONTROL	D		
C5	22-854	.0005 MFD.	R7	63-597	470 OHM	E		
C6	22-1049	.03 MFD.	R8	63-686	150 OHM WIREWOUND	F		
C7		20MFD. ELECTROLYTIC				G		
C8	22-1014	20MFD. ELECTROLYTIC				H		
R1	63-590	15M OHM	1	39576	WAVE MAGNET ASSEMBLY			
R2	63-579	220 OHM	2	39570	DETECTOR COIL ASSEMBLY			
			3	59571	OSCILLATOR COIL ASSEMBLY			

Models 6D612-6D612W-6D622-6D628

Zenith Radio Chassis No. 6B04

Operation	Connect Oscillator to	Dummy Antenna	Input Signal Frequency	Band	Set Dial At	Trimmers
1	Converter Grid	.5 mfd.	455 Kc.	BC	1600 Kc.	A, B, C, D
2	Single Turn Loop Coupled Loosely to Wave Magnet	.5 mfd.	1600 Kc.	"	1600 Kc.	F
3		.5 mfd.	1400 Kc.	"	1400 Kc.	H, G