



DIAG. NO.	PART NO.	DESCRIPTION	DIAG. NO.	PART NO.	DESCRIPTION	DIAG. NO.	PART NO.	DESCRIPTION
C1	22-1006	TWO-BAND VARIABLE	R3	63-1093	15 MEGOHM	5	95-697	2ND I.F. TRANS.
C2	22-829	.05 MFD.	R4	63-715	100 M OHM	6	142-31	PICKUP & PLUG
C3	22-162	.0001 MFD.	R5	63-719	470 M OHM	7	85-240	PHONO-RADIO SWITCH
C4	22-327	.02 MFD.	R6	63-713	47 M OHM	8	100-67	PILOT LIGHT 6.3V. .15A.
C5	22-492	.002 MFD.	R7	63-722	2.2 MEGOHM	9	95-713	FILTER CHOKE
C6	22-242	.01 MFD.	R8	63-726	10 MEGOHM	A		1ST I.F. TRANS. PRI.
C7	22-854	.0005 MFD.	R9	63-1112	VOLUME CONTROL	B		1ST I.F. TRANS. SEC.
C8	22-1049	.03 MFD.	R10	63-686	150 OHM WIREWOUND	C		2ND I.F. TRANS. PRI.
C9	22-1017	.05 MFD.	R11	63-1023	22 OHM WIREWOUND	D		2ND I.F. TRANS. SEC.
C10		20 MFD. ELECTROLYTIC	1		WAVE MAGNET ASSEMBLY	E	22-1015	WAVE TRAP
C11		20 MFD. ELECTROLYTIC	2	58326	WAVE TRAP COIL ASSEMBLY	F		BROADCAST OSC. (ON GANG)
R1	63-709	10M OHM	3	58356	DSC. COIL ASSEMBLY	G		BROADCAST ANT. (ON GANG)
R2	63-711	22M OHM	4	95-696	1ST I.F. TRANS.			

MODEL
6R583

SPEAKER
49-403 4"

I.F. FREQUENCY 455 KC.
6 TUBE SUPERHETERODYNE
CHASSIS No 6A08 - AC. PHONO
ZENITH RADIO CORPORATION