



NOTE- 9A ALTO
9B TREBLE
9C VOICE
9D NORMAL
9E LOW BASS
9F BASS

SPEAKER	MODEL
49-179-8*	75-323
49-251-10*	75-342
49-251-10*	75-343
49-208-10*	75-363
49-249-12*	75-366
49-266-12*	75-364

DWG NO	PART NO	DESCRIPTION	DWG NO	PART NO	DESCRIPTION	DWG NO	PART NO	DESCRIPTION	DWG NO	PART NO	DESCRIPTION
C-1	22-717	TAP WIND VAR COND	L-7	22-435	02 MFD	R-13	63-303	VOLUME CONTROL	6 NO		
C-2	22-889	50MFD	L-2	22-219	03 MFD	R-10	63-863	10M OHM	7		
C-3	22-182	0001 MFD	C-21	22-482	002 MFD	R-15		1/2 OHM MOUNTED IN TUNING TUBE BASE			
C-4	22-127	25 MFD	C-24	22-718	12 MFD ELECTROLYTIC						
C-5	22-170	.1 MFD	C-25	22-719	16 MFD ELECTROLYTIC	350V	1				
C-6	22-212	.05 MFD									
C-7	22-250	05 MFD									
C-8	22-59	TRIMMER COND					5-6204	ANTENNA COIL & SHIELD ARMOR			
C-9	22-740	COMPENSATING COND	R-1	63-621	39 OHM	1/4 W	3	5-6205	ORC COIL & SHIELD ARMOR		
C-10	22-708	DMIL FILLED PARACOND	R-2	63-592	33 M OHM	1/4 W	4	70-196	COMPENSATING COIL		
C-11	22-358	.002 MFD	R-3	63-597	470 M OHM	1/4 W	5		WAVE TRAP		
C-12	22-327	.02 MFD	R-4	63-596	47 M OHM	1/4 W	6	85-151	BAND SELECTIVE SWITCH		
C-13	22-182	00025 MFD	R-5	63-596	47 M OHM	1/4 W	7	85-536	1ST I.F. TRANSFORMER		
C-14	22-470	00015 MFD					8	85-537	2ND I.F. TRANSFORMER		
C-15	22-185	01 MFD	R-7	63-271	1 MEG OHM	1/4 W	9	5-6224	TUNE CONTROL SW ARMOR		
C-16	22-147	0005 MFD	R-8	63-655	220 M OHM	1/4 W	10	85-552	AUTOMATIC TUNING SWITCH		
C-17	22-438	006 MFD	R-9	61-296	220 M OHM	1/4 W	11	85-526	POWER TRANS-117-50-60 ~		
C-18	22-326	003 MFD	R-10	63-595	100 M OHM	1/4 W	12	85-535	POWER TRANS ALL VOLTAGE 25 ~		
C-19	22-190	.1 MFD	R-11	63-593	22 M OHM	1/4 W	13	100-16	PILOT LIGHT 25 A - 0.3 V		
C-20	22-444	006 MFD	R-12	63-884	3 SECTION CANNON		14		SPEAKER TRANS		

Chassis No. 5714

IF FREQUENCY 455 K.C.
7 TUBE SUPERHETERODYNE
CHASSIS NO 5714-A.C. 3-BAND
ZENITH RADIO CORPORATION

NOTE- TRIMMERS "C-X & N"
MOUNTED ON BAKELITE
STRIP-PARTS 1122-322