



I.F. FREQUENCY 455 KC.
 8 TUBE SUPERHETERODYNE
 CHASSIS N° 8A01 3BAND PHONO
 ZENITH RADIO CORPORATION

MODEL: 85586

QW#	PART #	DESCRIPTION	QW#	PART #	DESCRIPTION	QW#	PART #	DESCRIPTION	QW#	PART #	DESCRIPTION	
C1	22-927	TWO-GANG VARIABLE	C25	22-525	.005MFD.	1000K	R18	63-992	3-SECTION CANDOMM	17	85-203	DOOR SWITCH
C2	22-829	.05 MFD.	C26	22-523	.102 MFD.	600K	R19	63-151	15M OHM	18	85-191	MOTOR SWITCH
C3	22-828	.08 MFD.	C27	22-868	COMPENSATING COND.		R20	63-464	1 MEG OHM	19	3014E	LOOP LOADING COIL ASSEM.
C4	22-716	.0005 MFD.	C28	22-930	DUAL OSC. PADDER		R21	63-719	470M OHM	20	5752G	R.F. CHOKES
C5	22-727	.25 MMFD.					R22	63-717	220M OHM	A		12L1/2 TRANS. PRI.
C6	22-825	.1 MFD.	R1	63-529	10M OHM	1/2 W.	1			B		12L1/2 TRANS. SEC.
C7	22-812	.0025 MFD.	R2	63-574	33 OHM	1/4 W.	2	5750A	WAVEMAGNET ASSEMBLY	C		2091F - PRI.
C8	22-162	.0001 MFD.	R3	63-1077	18M OHM	1/4 W.	3			D		2091F - SEC.
C9	22-827	.1 MFD.	R4	63-593	47M OHM	1/4 W.	4	5750B	OSCILLATOR COIL ASSEMB.	E	22-958	BROADCAST OSC. (SEE NOTE 1)
C10	22-854	.0005 MFD.	R5	63-527	4700 OHM	1/4 W.	5	57507	OSC. COUPLER COIL ASSEM.	F		BROADCAST ANTENNA
C11	22-850	.02 MFD.	R6	63-595	100M OHM	1/4 W.	6	57449	AUTOMATIC TUNING ASSEM.	G		BROADCAST PADDER
C12	22-819	.03 MFD.	R7	63-649	18M OHM	1/4 W.	7	63-202	BAND SELECTOR SWITCH	J	22-463	BROADCAST ANTENNA
C13	22-816	.005 MFD.	R8	63-605	1000 OHM	1/4 W.	8	97559	WAVE TRAP COIL ASSEM.	K		SHORT WAVE OSC. (SEE NOTE 1)
C14	22-327	.02 MFD.	R9	63-271	1 MEG OHM	1/4 W.	9	63-711	WAVEMAGNET SWITCH	M		SHORT WAVE ANT. (SEE NOTE 2)
C15	22-954	.00035 MFD.	R10	63-711	22M OHM	1/4 W.	10	63-711	TELEVISION SWITCH	N		POLICE BAND OSC. (SEE NOTE 1)
C16	22-470	.00015 MFD.	R11	63-717	220M OHM	1/4 W.	11	63-158	PHONO SWITCH	Q		POLICE BAND ANT. (SEE NOTE 2)
C17	22-829	.005 MFD.	R12	63-595	100M OHM	1/4 W.	12	95-663	12L1/2 TRANS.			
C18	22-448	.004 MFD.	R13	63-597	470M OHM	1/4 W.	13	95-663	22L1/2 TRANS.			
C19	22-492	.002 MFD.	R14	63-117	1000 OHM	1/4 W.	14	58327	100-36 PILOT LIGHT 6.3K 25A.			
C20	22-326	.003 MFD.	R15	63-677	38M OHM	1/4 W.	15	100-80	100-80 PILOT LIGHT 110K 7W.			
C21	22-963	.002 MFD.	R16	63-796	10M OHM	1/4 W.	16	95-627	POWER TRANS. 50-60-117K.			
C22	22-719	1/8 MFD. ELECTROLYTIC	R17	60-376	60 OHM	1/4 W.						
C23	22-933	5MFD.										
C24	22-933	1/8 MFD.										

NOTES -
 (1) TRIMMERS K1-K4 ARE MOUNTED ON STRIP #22-850
 (2) TRIMMERS M1-M2 ARE MOUNTED ON STRIP #22-962