


PHONOLA RADIO - Mod. 624 - Gamma onde medie divisa: OM1 da 320 a 600 m, OM2 da 190 a 350 m. Gamma corte da 54 a 25 m, gamma cortissime da 27 a 13 m. Media frequenza 470 kc/s. Potenza d'uscita 7,5 W. Consumo 123 W.

Nomia.	Valore	Tolleranza %	Tensione di prova Volto	Tipo	Nomin.	Valore	Tolleranza %	Watt
C 1	2000 pf	+20 -10	3000	Carta	R 1	300 Ω	±10	1/2
C 2	15 "	±5	1500	Ag.	R 2	50.000 Ω	±10	1/4
C 3	15 "	±5	"	"	R 3	25.000 Ω	±10	2
C 4	15 "	±5	"	"	R 4	50.000 "	±10	1/2
C 5	50.000 "	+20 -10	"	Carta	R 5	1 M Ω	±10	1/4
C 6	15 "	±5	"	Ag.	R 6	0,5 M Ω	±10	1/4
C 7	15 "	±5	"	"	R 7	0,1 M Ω	±10	1/4
C 8	60.000 "	+20 -10	"	Carta	R 8	5.000 Ω	±10	1/2
C 9	50.000 "	+20 -10	"	"	R 9	50.000 Ω	±10	1/4
C 10	50 "	±5	"	Ag.	R 10	50.000 Ω	±10	1/2
C 11	20 "	±5	"	"	R 11	250.000 Ω	±10	1/4
C 12	250 "	±5	"	"	R 12	1000 "	±10	1/4
C 13	450 "	±5	"	"	R 13	1 M Ω	±10	1/4
C 14	20 "	±5	"	"	R 14	1 M Ω	±10	1/4
C 15	500 "	±5	"	"	R 15	1 M Ω	±10	1/4
C 16	740 "	±5	"	"	R 16	0,5 M Ω	±10	1/4
C 17	240 "	±5	"	"	R 17	80 "	±10	1/4
C 18	2 "	±5	"	"	R 18	0,1 M Ω	±10	1/4
C 19	250 "	±5	"	"	R 19	1 M Ω	Log. gov.	R. V.
C 20	250 "	±5	"	"	R 20	980 "	ecc. A. P.	—
C 21	240 "	±5	"	"	R 21	30.000 Ω	±10	—
C 22	240 "	±5	"	"	R 22	0,5 M Ω	Log. con. int.	R. T.
C 23	1,5 "	±5	"	"	R 23	1 M Ω	±10	1/4
C 24	25.000 "	+20 -10	"	Carta	R 24	50.000 Ω	±10	1/2
C 25	5.000 "	+20 -10	"	"	R 25	1.000 Ω	±10	1/4
C 26	100.000 "	+20 -10	"	"	R 26	250.000 Ω	±10	1/4
C 27	1000 "	+20 -10	"	"	R 27	220.000 Ω	±10	1/4
C 28	8 mf	+30 -20	500	Elett.	R 28	110 Ω	±10	1
C 29	50 pf	±5	1500	Ag.				
C 30	100.000 "	+20 -10	"	Carta				
C 31	100.000 "	+20 -10	"	"				
C 32	16 mf	+30 -20	350	Elett.				
C 33	8 "	+30 -20	500	"				
C 34	5.000 pf	+20 -10	3000	Carta				
C 35	5.000 "	+20 -10	3000	"				
C 36	25.000 "	+20 -10	1500	"				
C 37	25.000 "	+20 -10	"	"				
C 38	16 mf	+30 -20	350	Elett.				
C 39	25.000 pf	+20 -10	1500	Carta				
C 40	500 "	+20 -10	"	"				
C 41	25.000 "	+20 -10	"	"				
C 42	10.000 "	+20 -10	"	"				
C 43	100.000 "	+20 -10	"	"				
C 44	10.000 "	+20 -10	"	"				
C 45	50.000 "	+20 -10	"	"				
C 46	16 mf	+30 -20	350	Elett.				
C 47	16 "	+30 -20	350	"				
C 48	500 pf	+20 -10	1500	Carta				

624



ECH4



EBL1

AZ11WE54
AZ21WE53

ELENCO DELLE VALVOLE E TENSIONI

Valvola	Tipo	FUNZIONAMENTO	TENSIONI				
			VF	VP	VSCH	VC	VPO
V 1	ECH4	Amplificatrice AF - Amplificatrice BF	6,3	250	65	—	55
V 2	ECH4	Convertitrice	6,3	250	100	3,5	55
V 3	ECH4	Amplificatrice MF - Amplificatrice BF	6,3	200	75	—	75
V 4	EBL1	Rivelatrice C.A.V. - Amplificatrice finale BF	6,3	240	250	—	—
V 5	EBL1	Amplificatrice finale BF	6,3	240	210	—	—
V 6	WE53	Redditrice	4	—	—	—	—

