



PHONOLA 401

| | |
|-----|-------|
| V 1 | EK2 |
| V 2 | 6P7G |
| V 3 | 3BL1 |
| V 4 | WE 54 |

CAPACITA'

| n° | VALORI | TOLL. % | TENSIONE DI PROVA | TIPO |
|------|----------|------------|----------------------|--------|
| C 1 | 10000 pF | +20-10 | 1500 - | |
| C 2 | 200 pF | +10 | 1500 ~ | Ag |
| C 3 | 25 pF | +5 | 1500 ~ | Ag |
| C 4 | 412 pF | +1 | 1500 ~ | Ag |
| C 5 | 25000 pF | +20-10 | 1500 - | |
| C 6 | 25000 pF | +20-10 | 1500 - | |
| C 7 | 2 pF | +10 | 1500 ~ | |
| C 8 | 240 pF | -- | 1500 ~ | Ag |
| C 9 | 240 pF | -- | 1500 ~ | Ag |
| C 10 | 10000 pF | +20-10 | 1500 - | |
| C 11 | 10000 pF | +20-10 | 1500 - | |
| C 12 | 500 pF | +10 | 1500 - | |
| C 13 | 1 pF | +20-10 | 500 - | |
| C 14 | 10000 pF | +20-10 | 1500 - | |
| C 15 | 25000 pF | +20-10 | 3000 - | |
| C 16 | 10000 pF | +20-10 | 1500 - | |
| C 17 | 2 pF | +10 | 1500 ~ | |
| C 18 | 240 pF | -- | 1500 ~ | Ag |
| C 19 | 240 pF | -- | 1500 ~ | Ag |
| C 20 | 200 pF | +10 | 1500 ~ | Ag |
| C 21 | 25000 pF | +20-10 | 1500 - | |
| C 22 | 100 pF | +10 | 1500 ~ | Ag |
| C 23 | 5000 pF | +20-10 | 1500 ~ | |
| C 24 | 10000 pF | +20-10 | 1500 - | |
| C 25 | 1 μF | +20-10 | 500 - | |
| C 26 | 0.5 μF | +20-10 | 500 - | |
| C 27 | 5000 pF | +20-10 | 3000 ~ | |
| C 28 | 5000 pF | +20-10 | 3000 ~ | |
| C 29 | 8 μF | +30-20 | 525 - | Elett. |
| C 30 | 8 μF | +30-20 | 525 - | Elett. |
| C 31 | 25 μF | +30-20 | 30 - | Elett. |

RESISTENZE

| N° | VALORI | TOLL. % | WATT. |
|------|---------|------------|-------|
| R 1 | 250000Ω | + 10 | 1/4 |
| R 2 | 50000Ω | + 10 | 1/4 |
| R 3 | 20000Ω | + 10 | 1/4 |
| R 4 | 50000Ω | + 10 | 1/4 |
| R 5 | 25000Ω | + 10 | 1/4 |
| R 6 | 250000Ω | + 10 | 1/4 |
| R 7 | 1MΩ | + 10 | 1/4 |
| R 8 | 50000Ω | + 10 | 1/4 |
| R 9 | 10000Ω | + 10 | 1/4 |
| R 10 | 2500Ω | + 10 | 1/4 |
| R 11 | 50000Ω | + 10 | 1/4 |
| R 12 | 250000Ω | + 10 | 1/4 |
| R 13 | 400Ω | + 10 | 1/4 |
| R 14 | 1MΩ | + 10 | 1/4 |
| R 15 | 1MΩ | + 10 | 1/4 |
| R 16 | 1MΩ | + 10 | 1/4 |
| R 17 | 2200Ω | + 5 | 8 |
| R 18 | 110Ω | + 5 | 1 |
| R 19 | 50000Ω | + 10 | 1/4 |
| R 20 | 250000Ω | + 10 | 1/4 |
| R 21 | 250000Ω | + 10 | 1/4 |