



DIAG. NO.	PART NO.	DESCRIPTION	DIAG. NO.	PART NO.	DESCRIPTION	DIAG. NO.	PART NO.	DESCRIPTION	DIAG. NO.	PART NO.	DESCRIPTION
C1	22-1030	TWO GANG VARIABLE	C21	22-868	COMPENSATING COIL	R17	63-972	15M OHM 1W	A	22-1015	13T I.F. TRANS. PRI.
C2	22-289	50 MMFD. 600 V.	R1	63-260	100 M OHM 1/2 W.	R18	63-1056	200 OHM WIREWOUND 1 1/2 W.	B		13T I.F. " SEC.
C3	22-829	.05 MFD. 200 V.	R2	63-587	4700 OHM 1/2 W.	1		WAVEMAGNET ASSEMBLY	C		2ND I.F. " PRI.
C4	22-828	.05 MFD. 400 V.	R3	63-713	47 M OHM 1/2 W.	2	58404	ANTENNA COIL ASSEMBLY	D		2ND I.F. " SEC.
C5	22-182	.00025 MFD. 600 V.	R4	63-621	39 OHM 1/2 W.	3	58403	OSCILLATOR COIL ASSEMB.	E	22-1015	WAVE TRAP
C6	22-1037	DUAL PADDER 600 V.	R5	63-589	10M OHM 1/2 W.	4	58457	AUTOMATIC TUNING ASSRM.	F		BROADCAST OSC. (NOTE 1)
C7	22-825	.1 MFD. 400 V.	R6	63-605	1000 OHM 1/2 W.	5	85-228	BAND SELECTOR SWITCH	G		" ANT. (NOTE 2)
C8	22-327	.02 MFD. 200 V.	R7	63-599	1.5 MEG OHM 1/2 W.	6	58359	R.F. CHOKE & RES. ASSEM.	H		SHORT WAVE OSC. (NOTE 1)
C9	22-444	.004 MFD. 600 V.	R8	63-960	68 M OHM 1/2 W.	7	58326	WAVE TRAP COIL ASSEM.	K		" " ANT. (NOTE 2)
C10	22-228	.005 MFD. 800 V.	R9	63-719	470 M OHM 1/2 W.	8	95-703	1ST I.F. TRANSFORMER	M		POLICE BAND ANT. (NOTE 2)
C11	22-854	.00035 MFD. 600 V.	R10	63-1122	VOLUME CONTROL 600 V.	9	95-704	2ND I.F. TRANSFORMER	Q		NOTES:
C12	22-470	.00018 MFD. 600 V.	R11	63-399	47 M OHM 1/2 W.	10	58452	TONE CONTROL ASSEM. (LEFT)			(1) TRIMMERS F&K ARE MOUNTED ON STRIP #22-1033
C13	22-492	.002 MFD. 600 V.	R12	63-594	68 M OHM 1/2 W.	11	58451	TONE CONTROL ASSEM. (RIGHT)			(2) TRIMMERS G, J, M & Q ARE MOUNTED ON STRIP #22-1031
C14	22-684	.0005 MFD. 600 V.	R13	63-976	15 MEG OHM 1/2 W.	12	95-705	PWR. TRANS. 50-80W 117V			
C15	22-630	.02 MFD. 600 V.	R14	63-296	220 M OHM 1/2 W.	13	100-36	PILOT LIGHT 6.3V .25A.			
C16	22-219	.03 MFD. 200 V.	R15	63-597	470 M OHM 1/2 W.						
C17	22-827	.1 MFD. 450 V.	R16	63-975	82 OHM WIREWOUND 1/2 W.						
C18	22-1034	.5 MFD. ELECTROLYTIC 350 V.									
C19	22-1035	1 MFD. " 350 V.									
C20	22-1036	.14 MFD. " 450 V.									

I.F. FREQUENCY 455 K.C.
 7 TUBE SUPERHETERODYNE
 CHASSIS No 7A02 3 BAND A.C.
 ZENITH RADIO CORPORATION

MODELS: 75529, 75530, 75547,
 75557, 75558, 75559